

Code	Brief description	Description
01	Coffee grinder blocked	The coffee grinder is blocked (grinder blades jammed or sensor not reading properly)
03	Brewing unit blocked in 'work' position	Descent time-out exceeded
04	Brewing unit blocked in 'home' position	Ascent time-out exceeded
05	Water circuit blocked	No water in flow meter or flow meter not turning (jammed)
06	Frother unit solenoid valve	Frother unit solenoid valve short-circuit
07	Doser microswitch blocked	Doser microswitch short-circuit
10	Coffee boiler short-circuit	Coffee boiler temperature sensor short-circuit
11	Coffee boiler in open circuit	Coffee boiler temperature sensor in open circuit
12	Steam boiler short-circuit	Steam boiler temperature sensor short-circuit
13	Steam boiler in open circuit	Steam boiler temperature sensor in open circuit
14	Misc. temperature errors (coffee boiler)	Coffee boiler temperatures out of control
15	Misc. temperature errors (steam boiler)	Steam boiler temperatures out of control
16	Brewing unit short-circuit	Brewing unit microswitch short-circuit
17	Not used	
18	Not used	
19	No zero crossing	No zero crossing on card, could be caused by power board
20	Not used	